

List kompatibilných meničov a komunikácia s BMS pre typy batérií:

B-LFP48-200PW, B-LFP48-300PW, B-LFP48-100E 3U



Dokument vypracoval	Juraj Gerek
Distribútor:	ESOLAR, s.r.o.
Posledná modifikácia:	8.12.2025

CAN komunikácia:

číslo	Výrobca	Protokol
1	Pylon	PYLON CAN LV V1.3-2019.03.01
2	DEYE/sunsynk	PYLON CAN LV V1.3-2019.03.01
3	Growatt	Growatt CAN LV V1.09-2020.10.22
4	Victron	Victron CAN 2021.01.07
5	Luxpower	Luxpowertek CAN V1.0-2020.02.11
6	SMA	SMA CAN V2.0
7	GoodWe	GoodWe CAN Inverter LV V1.7-2020.02.28
8	Studer	STUDER CAN V1.02-2018.06.14
9	Sofar	SofarSolar CAN inverter V6
10	Ginlong/Solis	GINLONG CAN LV V1.0-2019.12.28
11	TBB_LITHIUM	TBB CAN V1.05-2021.04.20 & V1.1-2021.10.21
12	Daneng	DANENG CAN V10-2022.10.10
13	Aiswei	AISWEI CAN V1.0
14	SAJ	SAJ CAN V1.9-2022.06.30
15	MUST	MUST CAN V2.0.2-2021.06.02
16	Megarevo	PYLON CAN LV V1.3-2019.03.01
17	Afore	Afore CAN Hybrid Inverter V2.2-2023.06.02

RJ45 komunikácia:

číslo	Výrobca	Protokol
1	Pylon	PYLON RS485 LV-BPB V3.5-2019.08.07
2	DEYE/sunsynk	PYLON RS485 LV-BPB V3.5-2019.08.07
3	Growatt	Growatt RS485 V2.01-2019.02.13
4	Voltronic	Voltronic RS485 Inverter V1.0-2018.09.11
5	Phocos	Phocos RS485 2021.04.07
6	Luxpower	Luxpowertek RS485 inverter V0.3-2020.07.06
7	WOW	WOW RS485 Modbus V1.3-2017.06.27
8	Sorotec	Sorotec RS485 Inverter V1.22-2017.11.28
9	Hypon	HYPONTECH RS485 Modbus V2.0-2023.06.29
10	Afore	Afore RS485 Hybrid Inverter V1.02-2022.03.07

Prednastavená komunikácia batérie:

Komunikácia:

CAN	Victron
RJ845	DEYE

Nastavenia cez program od výrobcu:

s HS1.0.6 (Protocol code:HS-PACE-232-BP-V1.1)

Monitoring | Multi Monitoring | Memory Info. | Parameter Setting | **System Config.** | Export Datas

mV

Vref **Calibration**

Voltage **Calibration**

mA

Current (10000mA) **Calibration** **Resetting**

Current **Calibration** **Resetting**

Current (10000mA) **Calibration** **Resetting**

Cell Number Setting

Cell Number **Setting**

Current Setting

Current (A) **Setting** **Read**

Charge Setting

Gap Charge Threshold **Setting**

Capacity(mAH)

DesignCapacity

RemainCapacity

FullCapacity

Read **Write**

Battery Cycle Setting

Battery Cycle **Setting**

Inverter protocol

CAN Protocol

RS485 Protocol

Type



Read **Write**

Manufacture Information

Clear text box after writing

no-repeat BMS S/N 20 **V**

no-repeat PACK S/N (20) 20 **V**

BMS S/N: | PACK S/N: | COMM:  

Poznámka:

- Požiadajte svoj predajný tím o poskytnutie hesla pre prístup do administrácie softvéru na hostiteľskom počítači.
- Pri rôznych meničoch nie je rovnaké zapojenie pinov, preto kontaktujte dodávateľa meniča kvôli detailným informáciám o zapojení pinov konektora RJ45.

Ďakujeme